

# 901 PREAMPLIFIERS

## UHF PREAMP 14 DB F CONNECTOR (12 VDC)



Code : **9010009**

Model : **BR-411**

### Description

UHF preamplifier for the antenna box, powered through the coaxial cable. As well as amplifying the signals, it adapts the antenna impedance from 300 $\Omega$  to 75 $\Omega$ . The noise level is extremely low in order to amplify the signals without losing quality.

### Applications

Individual or MATV digital and analogue terrestrial TV installations where reception levels are very weak. The amplifier is installed as a replacement of the matching transformer of the antenna in order to amplify the signal before it is degraded by the attenuations of the installation. Its use achieves the best possible signal to noise ratio.

### Characteristics

Designed specially for MX, BU and AP antennas (except BU-260). Connection to the antenna by means of fast-on connections and to the coaxial cable by means of a screw terminal.

CODE		9010008	9010009	9010012
MODEL		BR-401	BR-411	BR-441
Inputs			1	
Frequency range	Band		UHF	
	MHz		470-862	
Gain	dB		14	
Maximum output level	dB $\mu$ V		100	
Noise figure	dB		1.4	
Input impedance	$\Omega$		300	
Output impedance	$\Omega$		75	
Output connection			F female	
Supply	V $\dots$	+24	+12	+5
	mA		8	
Protection index			IP 53	
Units per packaging			1	
Packing weight	Kg		0.04	
Packing dimensions	mm		160 x 120 x 30	